

Olympian Generator Sets GEP100-1

Generator Set Specifications

Standby	50 Hz: 70.4 kW (88 kVA) 60Hz: 80 kW (100 kVA)
Prime	50 Hz: 64 kW (80 kVA) 60Hz: 72 kW (90 kVA)
Voltage	380/220 to 220/127 Volts
Emissions/Fuel Strategy	Not Certified
Frequency	50 or 60 Hz
Speed	1500 or 1800 RPM

Engine Specifications

Engine Model	Perkins™ 1104A-44TG2
Compression Ratio	17.25:1
Aspiration	TA
Governor Type	Mechanical
Stroke	127 mm
Displacement	4.4 B
Bore	105 mm
Recommended Fuel	Class A2 Diesel or BSEN590